

**DURACELL**  
Rechargeable

**CEF22**

Charge Sizes: AA, AAA, C, D, 9V  
Charger for NiMH Batteries

**NiMH**

**Technical Specifications**



<b>Battery Charger:</b>	Class 2, Power Supply
<b>Plug:</b>	AC/DC Adapter Wall Plug
<b>Battery Type/Fit:</b>	NiMH: 1-8 AA/HR6, 1-8 AAA/HR03, 1-4 C/HR14, 1-4 D/HR20, 9V
<b>Typical Weight:</b>	599 g
<b>Input:</b>	100-240V AC, 50/60 Hz, 8W
<b>Output:</b>	AA/HR6 450 mA, AAA/HR03 450 mA, C/HR14 450 mA, D/HR13 450 mA, 9V 32 mA
<b>Operating Temp:</b>	0°C - 35°C (32°F - 95°F)
<b>Dimensions:</b>	203 mm (H) x 108 mm (W) x 60 mm (D)

**BENEFITS**

**Simple & Easy to Use “All-In-One” Charger for Multiple battery Sizes  
4 AA/AAA ready in 3 hrs.\***

**FEATURES**

**Charges AA, AAA, C, D, 9V NiMH batteries-LED Indicates Charge Status**

- Amber LED for AA, AAA, C, D, 9V
- Charges up to 8 batteries
- Charges multiple sizes

**LED Indicates Charge**

- Red LED for 9V
- Solid Red = Charging
- Green = Complete
- Flashing Red = Error/Abnormal battery or abnormal temperature

**Charger Automatically detects battery sizes at the same time**

**International Charge Capability- device can be used worldwide with suitable converter plug**

**SAFETY**

**Microprocessor Controlled**

- Charge Termination based on -dV/dt, temperature, and/or built in timer
- Primary Battery Protection- will not charge non-rechargeable batteries
- Over-temperature shut off- prevents overheating of battery
- Over-charge protection- prevents battery damage
- Low-voltage battery protection- prevents overheating and damage to battery
- Power protection circuit- resets whenever a battery is removed

**DURACELL**  
BATTERIES

Berkshire Corporate Park  
Bethel, CT 06801 U.S.A.  
Tel: Toll free 1.800.544.5454  
Web: [www.Duracell.com](http://www.Duracell.com)

\*Approx. 90% of full charge, when using Duracell AA1300 mAh NiMH Batteries.

Information and contents in this data sheet are for reference purposes only. They do not constitute any warranty and representation is subject to change without notice. For most current information and further details, please contact Duracell.

Document #: CH-A