

DURACELL
Rechargeable

CEF15

Charge Sizes: AA , AAA
Charger for NiMH Batteries

NiMH



Technical Specifications

Battery Charger:	Class 2, Power Supply
Plug:	Direct AC/DC adapter wall plug
Battery Type/Fit:	NiMH: 1 or 4 AA/HR6, 1 or 4 AAA/HR03
Typical Weight:	160 g
Input:	100-240V AC, 50-60 Hz
Output:	AA/HR6: 1.2V DC 6.5A per slot AAA/HR03: 1.2V DC 3A per slot
Operating Temp:	0°C - 35°C (32°F - 95°F)
Dimensions:	129 mm (L) x 82 mm (W) x 48 mm (H)

BENEFITS

Best in Class performance
4 AA/AAA batteries ready in 15 minutes*

FEATURES

Independent Channel Charging

- Four independent channels for any combination of AA and AAA batteries- Charger automatically detects battery
- Single battery charging capability
- Ensures a full charge regardless of charge or battery capacity

LED Indicates Charge

- Red = Charging
- Flashing Green = Battery ready for use*
- Green = Complete
- Flashing Red = Error/Abnormal battery or abnormal temperature

Maintenance Charge Keeps batteries Fresh & Emits Less Noise

International Charge Capability- device can be used worldwide with suitable converter plug

SAFETY

Microprocessor Controlled

- Charge Termination based on -dV/dt, temperature, and/or built in timer
- Primary battery protection- will not charge non-rechargeable batteries
- Over-temperature shutoff- prevents overheat of battery
- Over-charge protection- prevents battery damage
- Power protection circuit –resets whenever battery is removed or power is interrupted
- Low voltage battery protection- prevents overheat and damage to battery
- Reverse polarity protection- prevents battery charging in reverse

DURACELL
BATTERIES

Berkshire Corporate Park
Bethel, CT 06801 U.S.A.
Tel: Toll free 1.800.544.5454
Web: www.Duracell.com

*Approx. 75% of full charge, when using Duracell AA1300 mAh NiMH Batteries.

Information and contents in this data sheet are for reference purposes only. They do not constitute any warranty and representation is subject to change without notice. For most current information and further details, please contact Duracell.

Document #: CH-A